

Remote HMI USB Update

1. Download and unzip the latest version of the Remote HMI file from http://prominent.us/products/Controllers_Monitors/Cooling_Tower_Boiler_Controllers/SlimFlex5 to your Desktop
2. Navigate through the contents of the folder that you unzipped in Step 1 and find the folder named "site".
3. To confirm that the Files Attributes of the "site" folder are correct, follow the steps in the section below entitled "FILE ATTRIBUTE SETTINGS"

Caution: the controller also uses same "site" Attribute to update instruction manual, make sure you only have one "site" folder on your USB during update (site folder for "Remote HMI Update" or "instruction manual")
4. Copy the "site" folder
5. Insert a USB thumb-drive into your computer
6. Paste the "site" folder to the root of the USB thumb-drive
7. Eject your USB drive from your computer, then insert it into the controller's USB port
8. The OLED screen should display the message: "USB DRIVE ACTIVE". If the controller does not display this message, then remove the USB drive and try again.
10. Press F2 (UPDATE)
11. Press F2 (SITE)
12. Wait until the controller tells you to remove the USB drive
13. Open a web browser then go to <http://10.10.6.106> (or whatever the IP Address of your controller is)

```
*****
*****
***** FILE ATTRIBUTE SETTINGS *****
*****
```

To configure the File Attributes of the folders and files inside of and including the "site" folder, follow these steps:

1. Right-click the "site" folder
2. Select "Properties"
3. Click the "General" tab

4. Uncheck "Read-only"
4. Uncheck "Hidden"
5. Click the "Advanced..." button
6. Select "Folder is ready for archiving"
7. Select "Allow files in this folder to have contents indexed in addition to the file properties"
8. Uncheck "Compress contents to save disk space"
9. Uncheck "Encrypt contents to secure data"
10. Click the "OK" button
11. Click the "OK" button
12. In the "Confirm Attribute Changes" popup, select "Apply changes to this folder, subfolders and files"
13. Click the "OK" button
14. Done